

TAUP 2514-98
 5 August, 1998
 hep-th/9808030

**Non-Orthogonality of Residues
 in the
 Wigner-Weisskopf Model for Neutral K Meson Decay**

Eli Cohen and L.P. Horwitz*

Department of Physics and Astronomy
 Raymond and Beverly Sackler Faculty of Exact Sciences
 Tel Aviv University, Ramat Aviv 69978, Israel

Abstract: We review the application of the Wigner-Weisskopf model for the neutral K meson system in the resolvent formalism. The Wigner-Weisskopf model is not equivalent to the Lee-Oehme-Yang-Wu formulation (which provides an accurate representation of the data). The residues in the pole approximation in the Wigner-Weisskopf model are not orthogonal, leading to additional interference terms in the $K_S - K_L$ 2π channel. We show that these terms would be detectable experimentally in the decay pattern of the beam emitted from a regenerator if the Wigner-Weisskopf theory were correct. The consistency of the data with the Lee-Oehme-Yang-Wu formulation appears to rule out the applicability of the Wigner-Weisskopf theory to the problem of neutral K meson decay.

* Also at Department of Physics, Bar Ilan University, Ramat Gan, Israel

Lee, Oehme and Yang¹ constructed a generalization of the Wigner-Weisskopf² decay model in pole approximation, in terms of a two-by-two non-Hermitian effective Hamiltonian, leading to an exact semigroup law of evolution for the two channel K^0 decay. Wu and Yang³ developed, from this model, an effective parametrization of the $K^0 \rightarrow 2\pi$ decays, resulting in a phenomenology that has been very useful in describing the experimental results. Since the early 1970's, Monte Carlo reproduction of the data, establishing the parameter values, has been remarkably accurate in the energy 60-120 GeV of the kaon beam⁴.

We wish to point out that the Wigner-Weisskopf model² is, in fact, not consistent with the exact semigroup evolution assumed in the Lee-Oehme-Yang-Wu formulation, corresponding to exact semigroup evolution, even in pole approximation, and that the difference between the Wigner-Weisskopf prediction and semigroup evolution can, in principle, be seen experimentally. As we shall show, the experimental data rules out the applicability of the Wigner-Weisskopf theory. In this letter, we treat the $K_S - K_L$ 2π interference channel at the output of a regenerator. We consider elsewhere the structure of the two channel Wigner-Weisskopf model on the regeneration process itself⁵.

Regeneration systems are designed to reconstitute the K_S beam from a K_L beam in the order of $K_S : K_L \cong 10^{-3} : 1$, since the K_S beam decays rapidly with high branching ratio to 2π , while the K_L beam decays to 2π only on the order of 10^{-3} , the measure of CP violation.

The Wigner-Weisskopf model of particle decay (we first treat the one-channel case) assumes that there is an initial state in the Hilbert space representation of an unstable system; in the course of time, Hamiltonian action evolves this state, and the component that remains in the ϕ direction is called the survival amplitude:

$$A(t) = (\phi, e^{-iHt} \phi). \quad (1)$$

The Hamiltonian H includes a part H_0 for which the K -meson state is stationary, and a part H_I which corresponds to the part of weak interaction leading to the decay of the K -meson. We take the state ϕ to be a state of the neutral K -meson system (e.g., some linear combination of K^0 and $\bar{K}^0$); this eigenstate of H_0 is not stable under the full evolution H .

Defining the reduced resolvent, analytic for z in the upper half plane, in terms of the Laplace transform

$$\begin{aligned} R(z) &= -i \int_0^\infty e^{izt} (\phi, e^{-iHt} \phi) dt \\ &= (\phi, \frac{1}{z - H} \phi), \end{aligned} \quad (2)$$

we see that

$$(\phi, e^{-iHt} \phi) = \frac{1}{2\pi i} \int_C dz e^{-izt} (\phi, \frac{1}{z - H} \phi), \quad (3)$$

where C is a contour running from ∞ to 0 slightly above the real axis, and from 0 to ∞ slightly below. The lower contour can be deformed to the negative imaginary axis, providing a contribution which is small except near the branch point, and the upper contour can be deformed downward (with suitable conditions on the spectral function)

into the second Riemann sheet, where a resonance pole may appear. Assuming that the resonance contribution is large compared to the “background” integrals, the reduced motion of the survival amplitude is well-approximated by

$$(\phi, e^{-iHt}\phi) \cong g e^{-iz_0 t}, \quad (4)$$

where g is the t -independent part of the residue ($\approx$ unity), and

$$z_0 = E_0 - i \frac{\Gamma_0}{2}$$

is the pole position. It appears that this evolution could be generalized for the two channel case by replacing z_0 by an effective 2×2 non-Hermitian Hamiltonian. As we shall see, this structure is not generally admitted by the Wigner-Weisskopf model.

For the two-channel system, consider a state ϕ_i , $i = 1, 2$; let us calculate the decay amplitude $\phi_i \rightarrow |\lambda_j\rangle$, $j = 1, 2$, the continuum accessible by means of the dynamical evolution e^{-iHt} :

$$\sum_j \int d\lambda |\langle \lambda_j | e^{-iHt} | \phi_i \rangle|^2 = 1 - \sum_j |(\phi_j, e^{-iHt} \phi_i)|^2. \quad (6)$$

Here, the survival amplitude corresponds to the 2×2 matrix

$$A_{ij}(t) = (\phi_i, e^{-iHt} \phi_j).$$

This amplitude can be approximated in the same way as in (4) by estimating

$$(\phi_i, e^{-iHt} \phi_j) = \frac{1}{2\pi i} \int_C dz (\phi_i, \frac{1}{z - H} \phi_j) e^{-izt}. \quad (7)$$

It is convenient to write the 2×2 matrix reduced resolvent in the form

$$R_{ij}(z) = (\phi_i, \frac{1}{z - H} \phi_j) = \left(\frac{1}{z - W(z)} \right)_{ij}, \quad (8)$$

where $W(z)$ is a 2×2 matrix. It is almost always true (an exception is the matrix with unity in upper right element, and all others zero) that $W(z)$ has the spectral decomposition

$$W(z) = g_1(z)w_1(z) + g_2(z)w_2(z), \quad (9)$$

where $w_1(z)$ and $w_2(z)$ are numerical valued, and $g_1(z), g_2(z)$ are 2×2 matrices with the properties that

$$\begin{aligned} g_1(z)g_2(z) &= 0, \\ g_1^2(z) &= g_1(z), \quad g_2^2(z) = g_2(z), \end{aligned} \quad (10)$$

even though $W(z)$ is not Hermitian. These matrices are constructed from the direct product of right and left eigenvectors of $W(z)$, and form a complete set

$$g_1(z) + g_2(z) = 1. \quad (11)$$

Suppose now that the short lived K -decay channel has a pole at z_S . The matrix $W(z_S)$ (in the second Riemann sheet) can be represented as

$$W(z_S) = z_S g_S(z_S) + z'_S g'_S(z_S), \quad (12)$$

where $g_S g'_S = 0$, and the corresponding eigenvalues are denoted by z_S, z'_S . Then the reduced resolvent, in the neighborhood of $z \cong z_S$ has the form

$$R_{ij}(z) \cong \frac{1}{(z - z_S)(1 - w'_1(z_S))} g_S(z_S) + \frac{1}{(z - z'_S)(1 - w'_2(z_S))} g'_S(z_S), \quad (13)$$

where $w'_1(z), w'_2(z)$ are the derivatives of the eigenvalues of $W(z)$, of order the square of the weak coupling constant (these functions correspond to the mass shifts induced by the weak interaction). The residues are therefore $g_S(z_S)$ and $g'_S(z_S)$ to a good approximation. For the long-lived component, on the other hand, the pole occurs at z_L , and at this point,

$$W(z_L) = z_L g_L(z_L) + z'_L g'_L(z_L). \quad (14)$$

The reduced resolvent in this neighborhood is then

$$R_{ij}(z) \cong \frac{1}{(z - z_L)(1 - w'_1(z_L))} g_L(z_L) + \frac{1}{(z - z'_L)(1 - w'_2(z_L))} g'_L(z_L). \quad (15)$$

Since $W(z_S)$ and $W(z_L)$ correspond to the matrix-valued function $W(z)$ evaluated at two different points, although $g_S(z_S)$ and $g'_S(z_S)$ are orthogonal ($g_S(z_S)g'_S(z_S) = 0$), in general, $g_S(z_S)$ and $g_L(z_L)$ are not. If there were no CP violation, the matrix would be diagonal in the K_1, K_2 basis, and the two distinct idempotents would be structurally orthogonal even though they correspond to the decomposition of the matrix at two different points. One can estimate the product^{5,6}

$$\text{upper right element } g_S g_L = O(\alpha^3), \quad (16)$$

in a Lee-Friedrichs type model⁷, where α is the relative amplitude CP violation (independently of the strength of the weak interaction); the other matrix elements are of order α^4 or α^5 .

We now study the composition of the beam leaving a regenerator. We assume that in the design of such a system, the K_S component has amplitude approximately 10^{-3} compared to the amplitude of the K_L beam, so that non-trivial interference may occur. We represent the beam at the exit boundary of the regenerator as

$$|\psi\rangle_E = d_S |K_S\rangle + d_L |K_L\rangle, \quad (17)$$

where d_S and d_L are the amplitudes of the corresponding beam components. We assume that the evolution of the system (in vacuum) beyond this point is determined by the pole approximation of the two channel Wigner-Weisskopf reduced propagator,

$$U(\tau) = g_S e^{-i\kappa_S \tau} + g_L e^{-i\kappa_L \tau}. \quad (18)$$

Then, the action of $U(\tau)$ on the exit state is

$$U(\tau)|\psi\rangle_E = A_S(\tau)|K_S\rangle + A_L(\tau)|K_L\rangle, \quad (19)$$

where

$$\begin{aligned} A_S(\tau) &= (d_S \langle \tilde{K}_S | K_S \rangle + d_L \langle \tilde{K}_S | K_L \rangle) e^{-i\kappa_S \tau} \\ A_L(\tau) &= (d_L \langle \tilde{K}_L | K_L \rangle + d_S \langle \tilde{K}_L | K_S \rangle) e^{-i\kappa_L \tau}. \end{aligned} \quad (20)$$

It then follows that

$$|\langle 2\pi | U(\tau) \psi \rangle_E|^2 = |A_L|^2 \cdot |\langle 2\pi | K_L \rangle|^2 \left\{ 1 + \left| \frac{A_S}{A_L} \right|^2 \cdot \left| \frac{1}{\eta_{2\pi}} \right|^2 + 2\text{Re} \left(\frac{A_S}{A_L} \frac{1}{\eta_{2\pi}} \right) \right\}, \quad (21)$$

where, as usual,

$$\eta_{2\pi} = \frac{\langle 2\pi | K_L \rangle}{\langle 2\pi | K_S \rangle}. \quad (22)$$

The ratio of the amplitudes A_S and A_L is given, from (20) as

$$\left(\frac{A_S}{A_L} \right) \cong \left(\frac{A_S}{A_L} \right)^0 \left[1 + \left(\frac{d_L}{d_S} \right) \frac{\langle \tilde{K}_S | K_L \rangle}{\langle \tilde{K}_S | K_S \rangle} \right], \quad (23)$$

where we indicate the remainder for vanishing $\langle \tilde{K}_S | K_L \rangle$ by a superscript zero.

We see that the modification of the amplitude is not negligible. The ratio d_L to d_S , as we have pointed out, should be of order 10^3 so that the 2π interference can be seen; on the other hand, $\langle \tilde{K}_S | K_L \rangle$ is of order α^3 . We estimate this quantity by noting that the branching ratios⁸ are $K_L \rightarrow 3\pi \sim 10^{-1}$, $K_L \rightarrow 2\pi \sim 10^{-3} - 10^{-4}$ and $K_S \rightarrow 3\pi \sim 10^{-5} - 10^{-7}$, $K_S \rightarrow 2\pi \sim 10^{-1}$. Hence for K_L , the ratio $2\pi : 3\pi$ is $10^{-2} - 10^{-3}$ and for K_S the ratio $3\pi : 2\pi$ is $10^{-4} - 10^{-6}$. These ratios go as α^2 (the transition matrix elements (3.2) of ref. 6, a spectral model, includes the phase space factors, so that the amplitudes CP violating : CP conserving $\sim \alpha$), and we therefore take as a representative value for our estimate $\alpha^2 \sim 10^{-3}$, i.e., α^3 of order 10^{-4} . Moreover, $\langle \tilde{K}_S | K_S \rangle$ is of order unity. Hence the additional term is of order 10^{-1} , which, as we shall see, could, in principle, be observed. Substituting (23) into (21), one finds that

$$|\langle 2\pi | U(\tau) \psi \rangle_E|^2 = |A_L|^2 \cdot |\langle 2\pi | K_L \rangle|^2 \left\{ 1 + \left| \left(\frac{A_S}{A_L} \right)^0 \right|^2 \cdot \left| \frac{1}{\eta'_{2\pi}} \right|^2 + 2\text{Re} \left(\left(\frac{A_S}{A_L} \right)^0 \frac{1}{\eta'_{2\pi}} \right) \right\}, \quad (24)$$

where

$$\frac{1}{\eta'_{2\pi}} = \frac{1}{\eta_{2\pi}} \left\{ 1 + \left(\frac{d_L}{d_S} \right) \frac{\langle \tilde{K}_S | K_L \rangle}{\langle \tilde{K}_S | K_S \rangle} \right\}. \quad (25)$$

This correction to $\eta_{2\pi}$ which would emerge from an experimental study of the 2π decay would contain an approximate 10% deviation from the ratio (22). Furthermore, one may vary the experimental conditions slightly to produce a difference in the coefficients d_S and d_L by adding a thin sheet of additional regenerating material. Since

$$A_L \cong d_L \langle \tilde{K}_L | K_L \rangle e^{-i\kappa_L},$$

and we expect d_L to be relatively insensitive to such changes, the main variations of (24) are due to variations of $\zeta^{-1} = d_S/d_L \equiv \lambda e^{i\theta}$ in $(A_S/A_L)^0$ and $\eta'_{2\pi}{}^{-1}$. In particular,

$$\frac{\partial}{\partial \zeta} \frac{1}{\eta'_{2\pi}} = \frac{1}{\eta_{2\pi}} \frac{\langle \tilde{K}_S | K_L \rangle}{\langle \tilde{K}_S | K_S \rangle}, \quad (26)$$

since $\eta_{2\pi} = O(10^{-3})$, this derivative is $O(10^{-1})$. The effective $\eta_{2\pi}$ measured in this way would not be a constant relative amplitude, but it would be quite sensitive to variations in the regenerator structure ($\delta(1/\eta'_{2\pi}) \sim O(10^{-1})\delta\zeta$). The sensitivity to such changes can be seen by casting (24) into a form in which the phases and real amplitudes are explicit:

$$|\langle 2\pi | U(\tau) \psi \rangle_E|^2 = |A_L|^2 \cdot |\langle 2\pi | K_L \rangle|^2 \left\{ 1 + \left(\frac{b}{2}\right)^2 \left(1 + \frac{a}{b} \left[\frac{a}{b} + 2 \cos(\theta_{\tilde{S}L} - \xi_S - \theta) \right] \right) + \sqrt{\bar{a}^2 + \bar{b}^2} \sin(\gamma + \tau m_{LS}) \right\}, \quad (27)$$

where we have used the definitions:

$$\begin{aligned} \langle \tilde{K}_S | K_L \rangle &= K_{\tilde{S}L} e^{i\theta_{\tilde{S}L}} \\ a &= \frac{2K_{\tilde{S}L}}{|\eta_{2\pi}|m_L} e^{\frac{1}{2}\tau\Gamma_{LS}} & b &= \frac{2\lambda m_S}{|\eta_{2\pi}|m_L} e^{\frac{1}{2}\tau\Gamma_{LS}} \\ \Gamma_{LS} &= \Gamma_L - \Gamma_S & m_{LS} &= m_L - m_S \\ \kappa_{L,S} &= m_{L,S} - i\frac{\Gamma_{L,S}}{2} \\ \frac{d_S}{d_L} &= \lambda e^{i\theta} \\ \eta_{2\pi} &= |\eta_{2\pi}| e^{i\phi} & \eta'_{2\pi} &= |\eta'_{2\pi}| e^{i\phi'} \\ \langle \tilde{K}_S | K_S \rangle &= \mu_S e^{i\xi_S} & \langle \tilde{K}_L | K_L \rangle &= \mu_L e^{i\xi_L} \\ \bar{a} &= a \cos(\theta_{\tilde{S}L} - \xi_L - \phi) + b \cos(\xi_S - \xi_L + \theta - \phi) \\ \bar{b} &= -[a \sin(\theta_{\tilde{S}L} - \xi_L - \phi) + b \sin(\xi_S - \xi_L + \theta - \phi)] \end{aligned} \quad (28)$$

and

$$\gamma = \arctan\left(\frac{\bar{a}}{\bar{b}}\right). \quad (29)$$

A value of $\eta'_{2\pi}$ obtained in this way which is stable under variation of the regenerator structure would rule out the applicability of the Wigner-Weisskopf model to two channel

particle decays as exemplified in the neutral K meson system. The observed stability of $\eta_{2\pi}$ under a wide variation of regenerator configurations⁴ is consistent with the Lee-Oehme-Yang-Wu parametrization, and we therefore conclude that the Wigner-Weisskopf model is not applicable to the description of the decay of the neutral K -meson system.

Acknowledgements

We wish to thank I. Dunietz, C. Newton, B. Winstein, and T.T. Wu for helpful discussions.

References

1. T.D. Lee, R. Oehme and C.N. Yang, Phys. Rev. **106**, 340 (1957).
2. V.F. Weisskopf and E.P. Wigner, Zeits. f. Phys. **63**, 54 (1930); **65**, 18 (1930).
3. T.T. Wu and C.N. Yang, Phys. Rev. Lett. **13**, 380 (1964).
4. B. Winstein, *et al*, *Results from the Neutral Kaon Program at Fermilab's Meson Center Beamline, 1985-1997*, FERMILAB-Pub-97/087-E, published on behalf of the E731, E773 and E799 Collaborations, Fermi National Accelerator Laboratory, P.O. Box 500, Batavia, Illinois 60510.
5. E. Cohen and L.P. Horwitz, in preparation.
6. L.P. Horwitz and L. Mizrahi, Nuovo Cim. **21A**, 625 (1974).
7. K.O. Friedrichs, Comm. Pure Appl. Math. **1**, 361 (1948); T.D. Lee, Phys. Rev. **95**, 1329 (1956).
8. *Reviews of Particle Physics*, Phys. Rev. **D54**, 1 (1996).